

# LSS4 Fire Alarm Control Panel Operating Instructions

Facility Name: \_\_\_\_\_

Facility Address: \_\_\_\_\_  
\_\_\_\_\_  
\_\_\_\_\_

**Normal Condition:** The Power LED (Green) is on. All others lights are off.

**Alarm Condition:** System Alarm LED (Red) is on...  
Zone Alarm LED (Red) Flashes...  
Normal LED (Green) is off...

**1. To Silence Audible Devices** - Press the "ALARM SILENCE" switch. Audible signals turn off. Red LED change to steady code "1" appears on system display. New alarm zones will flash their LEDs and resound audible devices. To resound audible devices a second time, press "ALARM SILENCE".

**2. To Reset System** - Press "RESET" switch ( Only after investigation of alarm condition).

**Trouble Condition:** System trouble LED (Yellow) on...  
Zone trouble LED (Yellow) Flashes...  
System display indicates trouble code...  
Normal LED (Green) is off...  
Buzzer is on steady...

**To Silence Buzzer:** Press "Trouble Silence" switch. Code "2" appears on system display...

**To Clear Trouble:** System will automatically reset upon correction of trouble condition...

**Supervisory Trouble:** Supervisory LED (Yellow) is on...  
Zone LED (Yellow) flashes...  
Normal LED (Green) is off...  
Buzzer is on steady...

**Fire Drill:** Notify the Alarm Monitoring Center before conducting a fire drill

**1. To Drill & Sound all Audible Devices:** Press "DRILL / TEST" switch. Code "3" appears on the system display. All audible/visual devices will operate. Press "DRILL / TEST" a second time or "ALARM SILENCE" to end drill.

**For Service Contact:**

NAC DIVISIONS  
2014 Lincoln Way East  
Chambersburg, PA 17202  
717.261.0123